

WORKBENCH KEY UPGRADE PROCEDURE

(1) Create a new directory on your PC. (Desktop is fine)



(2) Extract .zip file to newly made folder. (In this case, the folder is named "Workbench key upgrade." (Ex: shows using WINZIP utility)

🗐 WinZip (Evaluation)	Version) - CTI k	ey update.z	ip	Extract View CheckOut Wizard Size Ratio Packed Path 69:52 AM 128 0% 128 41:30 PM 150 744 67% 52 733			
File Actions Option	ns Help						
New Open	Favorites	Add	Extract	View	Check	Out W	J izard
Name	Туре	Modifie	ed	Size	Ratio	Packed	Path
Authorize.dat	DAT File	4/11/20	16 9:52 AM	128	0%	128	
🛄 RemoteUpdateE	Application	1/20/20	14 1:39 PM	159,744	67%	52,733	

(3) Run (execute) file named remoteUpdateEmailUser.exe You should get a popup window like this:

		.,,
ĺ	Security Key Update Utility	×
l	Program Security Key	
\$	Exit	
ļ		

- (4) Make sure key to be programmed is now plugged in to an available USB port on your PC.
- (5) Click on "Program Security key"
- (6) You will get a confirmation window of the s/n of the key to be upgraded.

5	SERIAL NUMBER	×
	Security key - Serial Number: 1016 attached.	
I/C	ОК	

(7) If the process goes as planned, You will get a confirmation window confirming the process was done and your key upgrade process is complete.

Verification confirmation process

You can verify the date to which your newly upgraded key is now programmed to, by going into the help file within WORKBENCH software.



	R	
http://www.controltechnology.com Description: 2500 Series® Integrated Development Environment for IEC 61131-3 KSBusCampMaster.DLL version 1.0.0.11 KSBus2500ICo.DLL version 1.0.0.4 KSBus2500IO.DLL version 1.0.0.5 USB License Key #1016 Flags: 0 Ending Date: April 01, 2017		Indicates date which the USB key will support s/w versions of WORKBENCH and earlier. Note: If any release for WORKBENCH is released after th date, your USB key will not work with that version

Click on "About" tab and the following dialog window will be shown.

16DEC2016